

BS 7288:2016



BSI Standards Publication

**Specification for residual
current devices with or
without overcurrent
protection for socket-outlets
for household and similar
uses**

Publishing and copyright information

The BSI copyright notice displayed in this document indicates when the document was last issued.

© The British Standards Institution 2016

Published by BSI Standards Limited 2016

ISBN 978 0 580 93232 8

ICS 29.120.30; 29.120.50

The following BSI references relate to the work on this document:

Committee reference PEL/23/1

Draft for comment 16/30337150 DC

Publication history

First published August 1990

Second (present) edition November 2016

Amendments issued since publication

Date	Text affected
------	---------------

Contents

Foreword v

0 Introduction 1

1 Scope 1

2 Normative references 2

3 Terms, definitions and symbols 3

4 Classification 9

4.1 Classification according to behaviour resulting from failure of the line voltage 9

4.2 Classification according to the design 10

4.3 Classification according to behaviour in presence of d.c. components 10

4.4 Classification according to the provision for earthing 10

4.5 Classification according to the design of the cover plate 10

4.6 Classification according to the method of mounting 10

4.7 Classification according to the environmental conditions 10

4.8 Classification according to the type of terminals 11

4.9 Classification according to overcurrent protection 11

4.10 Type of SRCD 11

4.11 Number of poles 11

4.12 Type of switching 11

5 Characteristics of SRCDs 12

5.1 Summary of characteristics 12

5.2 Characteristics common to all socket-outlet residual current devices 12

5.3 Characteristics specific to SRCDs with overcurrent protection (see 4.9) 13

5.4 Preferred or standard values 14

5.5 *Text deleted* 15

6 Marking and other product information 15

6.1 General 15

6.2 Additional marking for screwless terminals 18

6.3 Void 18

7 Standard conditions for operation in service and for installation 18

8 Requirements for construction and operation 19

8.1 General 19

8.2 Information and marking 19

8.3 Mechanical and electrical design 20

8.4 Operating characteristics 25

8.5 Void 26

8.6 Test device 26

8.7 Temperature rise 27

8.8 Resistance to humidity 27

8.9 Dielectric properties 27

8.10 EMC compliance and unwanted tripping 27

8.11 Behaviour of SRCDs in case of overcurrent conditions 28

8.12 Resistance of the insulation against impulse voltages 28

8.13 Mechanical and electrical endurance 28

8.14 Resistance to mechanical shock 28

8.15 Reliability 28

8.16 Protection against electric shock and degree of protection IP of the SRCD 28

8.17 Resistance to heat 29

8.18 Resistance to abnormal heat and to fire 30

8.19 Behaviour of SRCDs within ambient temperature range 30

8.20 Resistance to temporary overvoltages 30

9	Tests	30
9.1	General	30
9.2	Marking and test of indelibility of marking	32
9.3	Verification of the trip-free mechanism	32
9.4	Test for the verification of electronic circuits	32
9.5	Requirements for capacitors and specific resistors and inductors	35
9.6	Test of reliability of screws, current-carrying parts and connections	35
9.7	Screwed and screwless terminals	36
9.8	Verification of the operating characteristics of type AC and type A SRCDs	47
9.9	Void	52
9.10	Verification of the test device	52
9.11	Verification of the limit of temperature rise	52
9.12	Resistance to humidity	55
9.13	Test of dielectric properties	56
9.14	EMC compliance and unwanted tripping	57
9.15	Verification of the behaviour of the SRCD under overcurrent conditions	58
9.16	Verification of clearances of the SRCD with the impulse withstand voltage test	65
9.17	Mechanical and electrical endurance	67
9.18	Resistance to mechanical shock	69
9.19	Reliability	72
9.20	Protection against electric shock and degree of protection IP of the SRCD	75
9.21	Resistance to heat	76
9.22	Resistance to abnormal heat and to fire – Glow-wire test	77
9.23	<i>Text deleted</i>	78
9.24	Verification of ageing of electronic components	78
9.25	Verification of the behaviour of the SRCD under temporary overvoltage conditions	78
9.26	Tests for reverse polarity (see 8.3.1)	79
9.27	Resistance to excessive residual stress test	79

Annexes

Annex A (normative)	Test sequence and number of samples to be submitted for verification of conformity	103
Annex B (normative)	Determination of clearances and creepage distances	107
Annex C (informative)	<i>Text deleted</i>	108
Annex D (normative)	Routine tests	109
Annex E (informative)	Methods of determination of short-circuit power factor	109
Annex F (informative)	Differences between BS 7822:2016 and IEC 62640:2011 (with the common modifications)	110

Bibliography	114
--------------	-----

List of figures

Figure 1 – Standard test finger	80
Figure 2 – General test circuit	81
Figure 3 – Minimum creepage distances and clearances as a function of peak value of voltage	82
Figure 4 – Minimum creepage distances and clearances as a function of peak value of operating voltage	83
Figure 5 – Pillar terminals	84
Figure 6 – Screw terminals and stud terminals	85
Figure 7 – Saddle terminals	86
Figure 8 – Saddle terminals	86
Figure 9 – Arrangement for checking damage to conductors	87
Figure 10 – Information for deflection test	88

Figure 11 – Example of a test circuit with current and voltage derived from separate sources	89
Figure 12 – Test cycle for low temperature test	89
Figure 13 – Void	89
Figure 14 – Test circuit for the verification of the correct operation of SRCDs, in the case of residual pulsating direct currents	90
Figure 15 – Test circuit for the verification of the correct operation of SRCDs, in the case of residual pulsating direct currents superimposed by a smooth direct current	91
Figure 16 – Damped oscillator current wave 0,5 μ s/100 kHz	92
Figure 17 – Example of test circuit for the verification of resistance against unwanted tripping due to surge currents to earth resulting from impulse voltages for SRCDs	92
Figure 18 – Test circuit for the verification of the rated making and breaking capacity and of the coordination	93
Figure 19 – Test apparatus for the verification of the minimum I^2t and I_p values to be withstood by the SRCD [9.15.2.1a)]	94
Figure 20 – Gauge for checking non-accessibility of live parts	95
Figure 21 – Impact-test apparatus	96
Figure 22 – Details of the striking element	97
Figure 23 – Mounting support for specimens	98
Figure 24 – Mounting block for flush-type SRCDs	98
Figure 25 – Reliability test cycle	99
Figure 26 – Ball-pressure test apparatus	100
Figure 27 – Sketches and table showing the application of the blows	101
Figure 28 – Diagrammatic representation of 9.22	102
Figure 29 – Test circuit for the verification of TOV withstand (9.25)	102
Figures B.1 to B.10 – Illustrations of the application of creepage distances	108

List of tables

Table 1 – Standard values of maximum break time of SRCDs for a.c. residual current	15
Table 2 – Standard values of maximum break time of SRCDs for pulsating d.c. residual current	15
Table 4 – Position of marking	16
Table 5 – Values of influencing quantities	19
Table 6 – Minimum clearances and creepage distances	22
Table 7 – Tripping current limits	26
Table 8 – Temperature-rise values	27
Table 11 – Withstand values and duration of temporary overvoltages	30
Table 12 – Test copper conductors corresponding to the rated currents	31
Table 13 – Type testing schedule	31
Table 14 – Maximum permissible temperatures under abnormal conditions	34
Table 15 – Screw thread diameters and applied torques	36
Table 16 – Relationship between rated current and connectable nominal cross-sectional areas of copper conductors	36
Table 17 – Values for flexing under mechanical load test for copper conductors	38
Table 18 – Values for pull test for screw-type terminals	38
Table 19 – Composition of conductors	39
Table 20 – Tightening torques for the verification of the mechanical strength of screw-type terminals	40
Table 21 – Relationship between rated current and connectable cross-sectional areas of copper conductors for screwless terminals	42

Table 22 – Value for pull test for screwless-type terminals	43
Table 23 – Values for flexing under mechanical load test for copper conductors	44
Table 24 – Test current for the verification of electrical and thermal stresses in normal use for screwless terminals	44
Table 25 – Nominal cross-sectional areas of rigid copper conductors for deflection test of screwless terminals	46
Table 26 – Deflection test forces	47
Table 27 – Tripping current ranges for SRCDs in case of pulsating d.c. current	51
Table 27A – Loading of SRCDs for temperature rise test	55
Table 28 – Tests to be applied for EMC	58
Table 29 – Tests to verify the behaviour of SRCDs under overcurrent conditions	59
Table 30 – Power factor ranges of the test circuit	61
Table 31 – Test voltage for verification of impulse withstand voltage between poles	66
Table 32 – Test voltage for verification of impulse withstand voltage with the metal support	66
Table 33 – Cross-sectional area for test conductors	67
Table 34 – Height of fall for impact tests	70
Table 35 – Torque test values for glands	72
Table A.1 – Type testing schedule	103
Table A.2 – Number of samples for full test procedure	105
Table A.3 – Number of samples for simplified test procedure	106
Table F.1 – Differences between BS 7288:2016 and IEC 62640:2011/HD 62640:2015	111

Summary of pages

This document comprises a front cover, an inside front cover, pages i to vi, pages 1 to 116, an inside back cover and a back cover.

Foreword

Publishing information

This British Standard is published by BSI Standards Limited, under licence from The British Standards Institution, and came into effect on 30 November 2016. It was prepared by Subcommittee PEL/23/1, *Circuit breakers and similar equipment for household use*, under the authority of Technical Committee PEL/23, *Electrical accessories*. A list of organizations represented on these committees can be obtained on request to their secretary.

Supersession

This British Standard supersedes BS 7288:1990, which remains current until 30 November 2019.

Relationship with other publications

This revision implements IEC 62640 with the common modification applied by HD 62640.

Information about this document

This standard reproduces the text of IEC 62640 with the common modifications set out in HD 62640 applied (this is why parts are labelled “void”) and certain necessary requirements retained from BS 7288:1990. The key differences between this edition of BS 7288 and IEC 62640 (with the common modifications) are set out in Annex F.

Where IEC 62640 text has been deleted as part of this revision, the words “*Text deleted*” have been inserted to indicate this.

This standard specifies requirements for socket-outlets incorporating residual current devices (SRCDs).

This edition covers the use of the following types of SRCDs:

- a) single pole with switched neutral;
- b) double pole;
- c) single pole with solid neutral.

Use of this document

It has been assumed in the preparation of this British Standard that the execution of its provisions will be entrusted to appropriately qualified and experienced people, for whose use it has been produced.

Presentational conventions

The provisions of this standard are presented in roman (i.e. upright) type. Its requirements are expressed in sentences in which the principal auxiliary verb is “shall”.

Commentary, explanation and general informative material is presented in smaller italic type, and does not constitute a normative element.

Contractual and legal considerations

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

Compliance with a British Standard cannot confer immunity from legal obligations.

0 Introduction

The BS EN 61008 and BS EN 61009 series are applicable to residual current devices having one to four poles used in any part of an electrical installation. These devices may be installed either at the origin of a whole installation or upstream of one or several circuits of a fixed installation or upstream of a circuit powering one or more socket-outlets, or be integrated in the same enclosure as a socket-outlet.

Such residual current devices are able to provide fault protection (protection against indirect contact), additional protection (protection against direct contact) if the rated residual current is equal to or less than 30 mA and protection against fire hazard due to a persistent earth leakage current without the operation of the overcurrent protection. Equipment meeting the requirements of the BS EN 61008 or BS EN 61009 series ensures isolation, withstands high levels of electromagnetic disturbances for household and similar applications, and allows safe use of an electrical installation.

Although the BS EN 61008 and BS EN 61009 series may be applicable to “residual current devices integrated in socket-outlets” it is acknowledged that due to the specific use and location of a socket-outlet, at the boundary of the fixed installation and immediately upstream of electrical equipment powered through a plug inserted into the socket-outlet, these devices require different features.

The residual current device at socket-outlet level is normally intended to be installed by skilled or instructed persons. It can be operated several times per day. The isolation function is not necessary since pulling out the plug from the socket-outlet is recognized as providing effective isolation. The absence of permanently connected long conductors downstream of the RCD, together with a limited number of powered appliances, justifies reduced EMC levels. Residual current devices covered by this standard are intended for additional protection in case of direct contact only. These particular features having been considered, it was recognized that a dedicated standard for socket-outlet residual current devices (SRCDs) was necessary.

1 Scope

This British Standard applies to residual current-operated devices (RCD) incorporated in, or specifically intended for use with, single pole and neutral and single pole and switched neutral and double pole socket-outlets, with provision of earthing of the socket-outlet for household and similar uses (SRCD: socket-outlet residual current devices). SRCDs, according to this standard, are intended to be used in single phase systems such as phase to neutral. SRCDs are only intended to provide supplementary protection downstream of the SRCD. SRCDs are intended for use in circuits where the fault protection and additional protection are already assured upstream of the SRCD.

NOTE 1 Void

NOTE 2 Void

NOTE 3 Void

SRCDs are neither intended to provide an isolation function nor intended to be used in IT systems.

NOTE 4 For SRCDs intended to provide isolation or fault protection, or to be used in IT systems, BS EN 61008-1 or BS EN 61009-1 should be used, as applicable, in conjunction with the requirements of BS 1363-2 for socket-outlets.

NOTE 5 Requirements and testing for SRCDs intended to be used in IT systems are under consideration.